

ENERGY 1000 START 230-400V code 829008

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks. Characteristics: choice of normal charge, quick charge (BOOST), quick start * timer for quick charge* remote control * display of charging and starting current * protection against overloads and polarity reversal.



AUTOMOTIVE



Technical Data

Standards:	LVD: EN 60335-2-29	EMC: EN 55014-1,2;	EMC: EN 61000-3-2,3				
CODE	V_{PH}	P_{C/S}	START	A_{EFF}	A_{EN}	A_{1V/C}	A_{START MAX}
829008	V50/60Hz 230 / 400 3 ph	kW 2,5 20	V 12 24	A 100	A 80	A 640	A 1000
C_{MIN/MAX}	C_{MIN/MAX}			kg	BAR CODE		
Ah 20 1200	Ah 20 800	5	mm(L,W,H) 380 560 885	kg 45	800489736539 8	pz/pallet 6	pz/pallet - B 4