

LEADER 150 START 230V 12V code 807549

Battery charger and starter for charging free electrolyte batteries (WET) with 12V voltage, and starting all types of petrol-driven vehicles. Characteristics: choice of normal charge, quick charge(BOOST), quick start * display of charging and starting current * protection against overloads and polarity reversal.



AUTOMOTIVE



Technical Data

Standards:	LVD: EN 60335-2-29	EMC: EN 55014-1,2;	EMC: EN 61000-3-2,3				
CODE	V_{PH}	P_{C/S}	START	A_{EFF}	A_{EN}	A_{1/IC}	A_{START MAX}
807549	V50/60Hz 230 1 ph	kW 0,3 1,4	V 12	A 20	A 14	A 80	A 140
C_{MIN/MAX}				BAR CODE			
Ah15h 25 250	2	mm(L,W,H) 225 290 205	kg 6,4	800489764147 8	pz/pallet 56	pz/pallet - B 42	